

TR42ADx5 - MODBUS MEMORY MAP

Add (Hex)	MODBUS REG. ADD (Dec)	Size	Description	Unit	Min	Step 1	Level 1	Step 2	Level 2	Step 3	Max	Initial Value	Format	Read/Write
0000	300001	1 W	Product Code	---	---	---	---	---	---	---	---	42	2	R
0001	300002	1 W	Product Model	---	---	---	---	---	---	---	---	4	1	R
0002	300003	1 W	Version Number	---	---	---	---	---	---	---	---	4,01	6	R
0003	300004	77 W	Reserved											
0050	300081	1 W	Command Operation Code	---	---	---	---	---	---	---	---	---	4200	W
0051	300082	1 W	Command Password	---	---	---	---	---	---	---	---	---	2	W
0052	300083	174 W	Reserved											
0100	300257	1 W	L1 Value	°C	0	1	---	---	---	---	219	135	1	R/W
0101	300258	1 W	L2 Value	°C	1	1	---	---	---	---	220	150	1	R/W
0102	300259	1 W	FAN1 Low Value	°C	0	1	---	---	---	---	219	100	1	R/W
0103	300260	1 W	FAN1 High Value	°C	1	1	---	---	---	---	220	110	1	R/W
0104	300261	1 W	RTD Connected	---	1	1	---	---	---	---	4	3	2	R/W
0105	300262	1 W	FAN Activation	---	0	1	---	---	---	---	4	3	4255	R/W
0106	300263	1 W	RTD For Command FAN1	---	0	1	---	---	---	---	4	2	4250	R/W
0107	300264	1 W	Weekly Automatic On FAN	---	0	1	---	---	---	---	1	0	4230	R/W
0108	400265	1 W	Slave Address	---	1	1	---	---	---	---	247	1	2	R/W
0109	400266	1 W	Com (RS-485) Baud Rate	---	3	1	---	---	---	---	7	3	6409	R/W
010A	400267	1 W	Com (RS-485) Configuration	---	2	1	---	---	---	---	7	2	6414	R/W
010B	400268	1 W	Password Request for Setpoint Modification	---	0	1	---	---	---	---	1	0	4230	R/W
010C	400269	1 W	FAN2 Low Value	°C	0	1	---	---	---	---	219	100	1	R/W
010D	400270	1 W	FAN2 High Value	°C	1	1	---	---	---	---	220	110	1	R/W
010E	400271	1 W	RTD For Command FAN2	---	0	1	---	---	---	---	4	2	4250	R/W
010F	400272	1 W	Delta FAN1/FAN2 (Advanced Mode)	°C	5	1	---	---	---	---	20	10	1	R/W
0110	400273	16 W	Reserved											
0120	400289	1 W	Buzzer Activation	---	0	1	---	---	---	---	2	0	4245	R/W
0121	400290	1 W	Output 4-20mA Channel	---	0	1	---	---	---	---	5	0	4246	R/W
0122	400291	1 W	Output 4-20mA Load	---	0	1	---	---	---	---	4	0	4247	R/W
0123	400292	221 W	Reserved											
0200	400513	1 W	RTD Input 1	°C	-10	0,1	---	---	---	---	240	---	3	R
0201	300514	1 W	RTD Input 2	°C	-10	0,1	---	---	---	---	240	---	3	R
0202	300515	1 W	RTD Input 3	°C	-10	0,1	---	---	---	---	240	---	3	R
0203	300516	1 W	RTD Input 4	°C	-10	0,1	---	---	---	---	240	---	3	R
0204	300517	1 W	Maximum RTD Input 1	°C	0	1	---	---	---	---	240	---	1	R
0205	300518	1 W	Maximum RTD Input 2	°C	0	1	---	---	---	---	240	---	1	R
0206	300519	1 W	Maximum RTD Input 3	°C	0	1	---	---	---	---	240	---	1	R
0207	300520	1 W	Maximum RTD Input 4	°C	0	1	---	---	---	---	240	---	1	R
0208	300521	6 W	Reserved											
020E	300527	1 W	Relay Status	BitField	---	---	---	---	---	---	---	---	4261	R
020F	300528	1 W	General Status (1st word)	BitField	---	---	---	---	---	---	---	---	4257	R
0210	300529	1 W	Only Local / Local+Remote Control	---	0	1	---	---	---	---	1	---	4241	R
0211	300530	8 W	Reserved											
0219	300538	1 W	General Status (2nd word)	BitField	---	---	---	---	---	---	---	---	4260	R
021A	300539	9 W	Reserved											
0223	300548	1 W	User Logged	---	0	1	---	---	---	---	1	0	4242	R
0224	300549	29 W	Reserved											
0241	300578	1 W	4mA Calibration Correction Factor	---	800	1	---	---	---	---	1200	1000	2	R
0242	300579	1 W	20mA Calibration Correction Factor	---	800	1	---	---	---	---	1200	1000	2	R

TR42ADx5 - COMMANDS				
VALUE	DESCRIPTION	LEVEL PSW	PRESET	NOTES
0	No commands	-		
16	Maximum Temperature CLEAR	user		

TR42ADx5 - FORMATS

Format Code	Type	Value	Definition
F1	Integer		Signed Integer Value
			Example: -123 saved as -123
F2	Integer		Unsigned Integer Value
			Example: 123 saved as 123
F3	Integer		Signed Integer Value with 1 decimals
			Example: -1.0 saved as 10
F4	Integer		Unsigned Integer Value with 1 decimals
			Example: 1.0 saved as 10
F5	Integer		Signed Integer Value with 2 decimals
			Example: -1.00 saved as -100
F6	Integer		Unsigned Integer Value with 2 decimals
			Example: 1.00 saved as 100
F4230	Integer		FAN Weekly Activation Format Password Request for Setpoint Modification Format
		0	Disabled
		1	Enabled
F4241	Integer		Only Local / Local+Remote Control
		0	Local Only
		1	Remote + Local
F4242	Integer		User Status
		0	Not Logged
		1	Logged
F4245	Integer		Buzzer Activation Format
		0	DISABLE
		1	L1
		2	L2
F4246	Integer		4-20mA Output Channel Format
		0	SCAN
		1	HOT
		2	PT1
		3	PT2
		4	PT3
		5	PT4
F4247	Integer		4-20mA Output Load Format
		0	100R
		1	200R
		2	300R
		3	400R
		4	500R
F4250	Integer		RTD for command Fan Format
		0	1 - - -
		1	1 2 - -
		2	1 2 3 -
		3	1 2 3 4
		4	- - - 4
F4255	Integer		Fan Activation Format
		0	OFF
		1	Fan 1
		2	Fan 2
		3	All
		4	Advanced

F4257	16 Bits BitMap		General Status Bits 1st word
		Bit 0	L1 Active
		Bit 1	L2 Active
		Bit 2	FAN1 Active
		Bit 3	FAULT Active
		Bit 4	FAN1 WEEKLY Active
		Bit 5	FAN1 MANUAL FUNCTION Active
		Bit 6	BUZZER Active
		Bit 7	Not Used
		Bit 8	INPUT RTD 1 Failure - Fco
		Bit 9	INPUT RTD 2 Failure - Fco
		Bit 10	INPUT RTD 3 Failure - Fco
		Bit 11	INPUT RTD 4 Failure - Fco
		Bit 12	INPUT RTD 1 Failure - Fcc
		Bit 13	INPUT RTD 2 Failure - Fcc
		Bit 14	INPUT RTD 3 Failure - Fcc
		Bit 15	INPUT RTD 4 Failure - Fcc
F4260	16 Bits BitMap		General Status Bits 2nd word
		Bit 0	FAN2 Active
		Bit 1	FAN2 WEEKLY Active
		Bit 2	FAN2 MANUAL FUNCTION Active
		Bit 3 ~ Bit 15	Not Used
F4261	16 Bits BitMap		Output Relay Status Bits
		Bit 0	L1
		Bit 1	L2
		Bit 2	FAULT
		Bit 3	FAN1
		Bit 4	FAN2
		Bit 5 ~ Bit 15	Not Used
F6409	String		BaudRate Value
		3	9600 Bps
		4	19200 Bps
		5	38400 Bps
		6	57600 Bps
		7	115200 Bps
F6414	Integer		RS Port Configuration
		2	8N1 (8 bits Data, Parity NONE, 1 bit Stop)
		3	8N2 (8 bits Data, Parity NONE, 2 bit Stop)
		4	8E1 (8 bits Data, Parity EVEN, 1 bit Stop)
		5	8E2 (8 bits Data, Parity EVEN, 2 bit Stop)
		6	8O1 (8 bits Data, Parity ODD, 1 bit Stop)
		7	8O2 (8 bits Data, Parity ODD, 1 bit Stop)