

1800 428 699

Portable Petrol Generator with E-Start FP8000HSRF

8 kVA Honda Powered Petrol Generator with E-Start

8 kVA portable generator powered by Honda petrol engine with electric start. It is the perfect size for almost everything, with 2 x 15 amp outlets, and Honda Australia Approved GX390 engine, this generator will run your power tools, compressor, Welder and much more.

Specifications

8 kVA **Power Rating: Alternator Rating:** 9.5 kVA

Honda GX390 **Engine Model:**

Phase: 1 phase

Starting System: Recoil/Electric

6.1 L **Fuel Tank Capacity:**

Noise Level @ 7m: **74 dBA**

Outlets: 2 x 15 Amp

Volts: 230 V

2.58 L/Hr Approx. Fuel Consumption @ 80% Load:

2.36 hrs Operation Hours @ 80% Load:

Petrol **Fuel Type:**

Dimensions: 810 x 545 x 545 mm

Weight: 85 kg

*Specifications are subject to change without notice







www. gentechgenerators.com.au