



About The P2200i Inverter

Pramac P2200i Inverter: This generator provides clean and stable power for sensitive electronics. It is easy to carry, fuel efficient and has low noise levels. Includes:

- Equipped with an OHV engine which provides consistent power for multiple applications.
- Inverter technology means stable power for safe operation of sensitive electronics.
- Pramac P2200i Economy Mode automatically adjusts the engine speed to the optimum level – this provides excellent fuel economy and noise reduction.

P2200i Inverter

Max power	2100 W
Rated power	1900 W
Engine	Stage V, 3000 rpm, 4 stroke
Starting system	Recoil
Voltage regulation system	Inverter
Fuel	Petrol
Tank capacity	4.5L, Fuel gauge, Fuel filter
Running time 75%:	4.5 h
Noise pressure level	@ 7 m 68 dB(A)

Control Panel:

- Selector switch: O/I, Air choke valve, Economy mode
- Digital Display: Voltmeter, Frequency meter, Hourmeter
- Protections: Overload, oil guard (with lamp)
- Outputting energy (indicator light – Green)
- Overloading and Oil alarming (indicators light – Red)

Sockets:

- 1 x UK Domestic Socket [BS1363 (13A) IP54]
- DC 12V 8A
- n°2 USB DC 5V 2A