

Ohmite Resistor Guide

Surface Mount		Part Number Prefix	Ω	Watts	Wirewound		Part Number Prefix	Ω	Watts
	HVF	HVF1206-HVF2512	1K-100G	0.3-1.0		20	20J-27J	0.1-100K	1.0-10.0
	LVC	LVC06-LVC25	0.01-0.976	0.25-1.0		40	40F-45F	0.1-150K	1.0-10.0
	MMC	MMC06-MMC25	47-51M	0.1-1.0		80	80F-85F	0.1-150K	1.0-10.0
	MC	MC101-MC204	100-5G	0.75-3.25		RW (MIL)	RW70-RW79	0.1-150K	1.0-10.0
	60S	602SJR-610SJR	0.002 - 0.01	0.25-1.0		89	805F-850F	0.005-100K	5.0-50.0
	MC1RD	MC1RD	5M-5G	1.5		90	90J- 95J	0.1-91K	1.5-11.0
	RC	RC0S2-RC1R0	2.2-20M	0.25-1.0		Axiohm	1C-10C	0.1-90K	1.0-10.0
	RF	RF0S8-RF1S0	1-10M	0.8-1.0		G	GW10-GW13	1K-75K	10.0-13.0
	RP	RP1S3-RP3R0	1-1M	1.25-3.0		HS/HSN	HS100-HS250	0.05-35.7K	100-250
	RW	RW1S0-RW3R5	0.005-25K	1.0-3.5		Metalohm	20/45M - 60/115M	0.05-81K	20-115
	RW (2010)	RW0S6	0.005-1K	0.6		PC-58	R3J-R5J	1-20K	3.0-5.25
	RW1/RW2	RW1S0CK-RW2S0DK	0.005-0.05	1.0-2.0		WFH	WFH90 - WFH330	0.22-39K	90-330
	TDH	TDH35	0.1-5K	35		200	B5J-B20J	0.03-100K	5.0-20.0
	WL	WLA-WLC	0.005-0.1	0.5-2.0		210	D12K-D1000K	1-100K	12.0-1000
	WH/WN	WHA-WHC/WNA-WNC	0.1-8K	0.5-2.0		250	F10J-F55J	1-50K	10.0-55.0
	CS3	CS3F/J/K	0.001-0.05	3		270	L12J-L1000J	0.1-392K	12.0-1000
	10	12F-15F	0.005-0.25	2.0-5.0		280	C35K-C2000K	0.02-358	35-2000
	10 (4 Term.)	13F-17F	0.005-0.1	3.0-7.0		HPW Precision WW	101A-520A	0.1-43M	0.05-2.0
	60	600HR-630HR	0.005-0.1	0.1-3.0		14A	14A	0.004-0.051	4
	60 (4 Term.)	610-650	0.002-0.05	1.0-5.0		HSP Precision WW	HS185A-HS520A	10-43M	0.125-1.5
	FCSL	FCSL64-FCSL90	0.001-0.05	2-4					
	LVK	LVK12-LVK25	0.001-0.5	0.5-2.0					
www.ohmite.com		Tel: 1-866-964-6483	Fax: 1-847-574-7522						
		Int'l: 1-847-258-0300	info@ohmite.com						

Thick Film/Heatsink		Part Number Prefix	Ω	Watts	Wirewound		Part Number Prefix	Ω	Watts
	TA	TA100-TA810	0.10 - 250K	3.0-100		P Series Precision WW	PAA-PGZ	1-15M	0.125-2.0
	TAH	TAH20	0.05-10K	20		TUW	TUW3J-TUW15J	0.01-1K	3.0-15.0
	TBH	TBH25	2-10K	25		TWW	TWW3J-TWW10J	0.01-990	3.0-10.0
	TCH	TCH35	0.1-10K	35		Metal Oxide TUM/TWM	TUM3J-TUM15J	43-50K	3.0-15.0
	TDH	TDH35	0.1-10K	35		TWM3J-TWW10J	180-150K	3.0-10.0	
	TEH	TEH70	2-10K	70		WW/Hi Energy	Part Number Prefix	Ω	Joules
	TEH100	TEH100	0.05-1K	100		30	30J-35J	1-150	1.9-162
	TFH	TFH85	2-10K	85		825	825J	1-150	11-51
	TGH	TGHHV-TGHLX	0.1-10K	120-200		RH	RH3R0	0.5-75	2-12.9
	TGHG	TGHG	0.0005-0.1	100	Composition/High Energy		Part Number Prefix	Ω	Joules
	TK	TK20	0.03-10K	20		Little Demon	OA-OF	2.2-20M	0.1
	TN	TN15P-TN15X	4-10K	15		OX/OY	OX-OY	3.3-1M	50-80
	TL	TL54 - TL122	0.5-51K	27-275		A	AW-AZ	1-1K	400-2800
	TAP600	TAP600	1-10K	600	Thick Film/High Energy		Part Number Prefix	Ω	Joules
	TAP800	TAP800	1-10K	800		TFS	TFSA-TFSF	100-100K	3.0-11.0
	TAP1000	TA1K0PH	3-50	1000	Thick Film/High Voltage		Part Number Prefix	Ω	Volts
	Variable Voltage Controls	Part Number Prefix	Ω	Watts		Super Mox	MOX910-MOX970	1K-50G	15K-90K
	C	CA-CMU	50-5M	2		Slim Mox	SM100-SM410	100-5G	1.5K-25K
	A	AS-ASM	50-5M	0.5		Mini Mox	MOX400 - MOX1125	500-1T	2.5K-7.5K
	R	RCL-RUS	0.5-50K	7.5-1000		Mini Mox E	MOX200-MOX300	100K-1.5M	0.5K-1K
						Maxi Mox	MOX-1-12 - MOX-5-13	250-1T	10K-50K
						Power Mox	MOX-F - MOX-J	20K-1T	20K-60K
						Power Mox Div.	MOX-FRD - MOX-JRD	1K-1T	20K-60K
						RX-1M	RX-1M	1M-1T	1K
					WW/High Current		Part Number Prefix	Ω	Watts
	PFE/PFR	PFE2K-PFR8K	0.033-42.1	200-1.6K					
	14984	14984-10-01/03/04/07	0.118-0.285	2.8K-3.1K					
	WLRD6G	WLRD6G	0.0426-6.13	525-1750					

OHMITE®

March 2010