

# ***How to specify the Frame & Mullions (F&M) Adjustable Mullion Receptacle Threshold Assembly in Finish Hardware Division 08 71 00:***

**Acceptable Manufacturers:** Frame & Mullions LLC (F&M) POC is Howard Wright / 804-651-7355 / [Howard.Wright@whwmktg.com](mailto:Howard.Wright@whwmktg.com).

## **Product Description:**

**Thresholds for removable 2" x 3" mullions with radiused corners:** Solid extruded aluminum. 5/16" thick x 1/2" height x 9 1/2" wide Adjustable Mullion Threshold Assembly. It Incorporates a two-piece 4" x 4 1/2" Adjustable Mullion Receptacle which includes a two-sided 2" x 3" x 3/8" adjustable Safety Block. One side of the Safety Block receives the mullion and then can be easily removed and flipped over to provide a flush threshold surface when the mullion is temporarily removed. For exterior doors, the threshold should extend out beyond the width of the opening to equal the width of the exterior frame face, both sides.

## **How to specify in Finish Hardware Sets:**

Option 1 (for complete assembly, threshold and adjustable mullion receptacle):

1 Threshold w/Mullion Recep	MR-T-ADA-95	F&M
-----------------------------	-------------	-----

Option 2 (for the adjustable mullion receptacle only, when a threshold is not desired but a removable 2" x 3" mullion is required):

1 Mullion Receptacle	MR-X-ADA-95	F&M
----------------------	-------------	-----

Option 3 (for threshold only, when mullion not needed, either for pair of doors or single door opening):

1 Mullion	ADA-95	F&M
-----------	--------	-----